

250mm

Relacart®
— Real Sound Always




M-C36
User Manual

Thank you!


Thank you for choosing relacart M-C36 condenser microphone module. M-C36 is suitable for Relacart UR series handheld wireless transmitters, excellent off-axis directional, high sound pressure suitable frequency response curve restore various sounds accurately, whether it is speech or singing, can meet your needs and give you a true sound. The M-C36 condenser microphone module is compatible with Shure® wireless microphone body.

M-C36 is a precision vocal microphone module. It adopts a cardioid directional condenser microphone core design, which can be flexibly matched with a variety of handheld transmitters. It is specially designed for relacart H series handheld transmitters and can provide a flat frequency response and high sound pressure level processing capability. It has a warm and natural sound quality. The advanced anti-vibration system of the microphone head can absorb mechanical vibrations and minimize the touch noise. It can provide excellent rear attenuation for personal monitoring environment, and accurately restore various sounds. The microphone mesh cover is made of elastic steel wire and has a built-in windshield, which can effectively reduce unwanted wind noise and breath noise.

Frequency Response



Polar Pattern



Product specification

relacart UR series wireless
Connectivity: microphone body
Shure® wireless microphone body

Type: Condenser

Directivity: cardioid

Frequency Response: 100-18000Hz

Flexibility: -52dB re 1V/Pa

Max SPL: 145dB@1%

Dimension: 51mmx74mm

Weight: 145g

Safety and maintenance



Please make sure that the equipment connected to your M-C36 complies with the safety regulations implemented in your country.

Support

If you have any inquiries or questions about your Relacart product, please contact us directly:
<http://www.relacart.com/contact>

This product complies with the standards listed in the declaration of conformity. Technical data are subject to change without notice.



70mm

250mm

Relacart® 力卡
— Real Sound Always




Most Sincerely,
Your relacart Team
您最真诚的 relacart 团队

感谢!


感谢您选择relacart M-C36电容话筒模组。M-C36适用于Relacart UR系列手持式无线发射器，优异的离轴指向性，高声压耐受和适合的频率响应曲线准确还原各种声音，无论演讲或者演唱都能满足您的需求，给您真实的声音还原。M-C36电容话筒模组可兼容Shure® 无线麦克风主体。

M-C36是一款精密的人声话筒模组，它采用心型指向电容咪芯设计，可以灵活匹配多种手持发射机，并能够提供非常平直的频率响应和高声压级处理能力。它具有温暖自然的音质，先进的话筒头防震系统能够吸收机械振动，并将触摸噪声降低到最小，能够为个人监听环境提供出色的后方衰减，并准确的还原各种声音。话筒网罩使用弹性钢丝制成，内置防风罩，能有效地降低不必要的风声和呼吸噪声等。

频率响应



极性响应



技术规格

连接: relacart UR系列无线麦克风主体
Shure® 无线麦克风主体

类型: 电容

指向: 心型

频率响应: 100-18000Hz

灵敏度: -52dB re 1V/Pa

最大声压级SPL: 145dB@1%

尺寸: 51mm x 74mm

重量: 145g

安全与维护



请确保您的M-C36所连接的设备符合贵国实施的安全规定。

支持

如果您的relacart产品出现任何问题或有任何疑问，请直接与我们联系：
<http://www.relacart.cn/contact>

本产品符合《合格声明》所列标准。
技术资料如有更改，恕不另行通知。



70mm

双面：250 x 70 mm，100克书写纸
红色框：说明书尺寸
红色虚线：折叠位置（风琴折法）